

Service Mode – Setting Instructions for ET30 Digital Timer

To access service mode remove the coin box, press and release switch 'B' until the display changes to 'St 01'

St 01 - sets the amount of time given by the L2 token coin

St02 - sets the amount of time given by a €1 coin

St03 - displays the total amount of tokens/money inserted

St04 - displays the total amount of credit given since the last factory reset

To View or Change Time Settings

Press and release Button 'B' to step to the desired setting number (St01 for Tokens and St02 for €1 Coins)

When the required number is showing on the display press and release 'A' to display the current setting. Press and release 'A' to select the digit to be changed then press and release 'B' to alter that digit. When the required setting is showing on the display replace and lock cash box, your new setting will then be automatically stored.

Error Messages ET30 Digital Timer

- 01 Opto 1 detected an object not conforming to the required parameters
- 02 Opto 2 detected an object not conforming to the required parameters
- 03 IIC communication error talking to the non-volatile memory
- 04 Not used – Now replaced with ‘Sync’ message. See below
- 05 Opto 1 validated but meter is configured incorrectly
- 06 Opto 2 validated but meter is configured incorrectly
- 07 Opto 1 validated but St.01 is zero
- 08 Opto 2 validated but St.02 is zero
- 09 Not used
- 10 Not used
- 11 Not used
- 12 Not used
- 13 System Error – Mode routine entered with invalid ‘mode’ value
- 14 System Error – Temp mode routine entered with invalid ‘Temp mode’ value
- 15 System Error – ‘Add Mc’ entered with zero ‘Coin Value’
- 16 System Error – IIC routines internal error

If any of the error messages 13 – 16 are encountered please contact the D H Meters Ltd technical department